

ELECTRIC MAXIDOOR TROUBLE-SHOOTING
MOTOR AUTO-REVERSES

<u>Model Nos:</u>	MkI &II MkIII;	Unlabeled EY/9/97	
<u>Motor:</u>	MkI, II & III (Short Hand Crank)	220V, 1 phase 380V, 3 phase	W1000, 550w, 32rpm, D1000, 740w, 32rpm D1000/2, 1500w, 52rpm.
	Note: Long Hand Crank from Del. No. 63782 (Invoice No. 33864), dated 5-5-00		

Units with Standard Contactor Box with Open, Closed and Stop Buttons.

Fault

Door automatically begins to open when it reaches the closed position

Cause

Short circuit between contactors (under open/closed/stop buttons)

Remedy

Check wire connection inside contactor box; black box containing limit switches found on top of electric motor; and the wire in-between these units. In particular any wires emanating from terminals 5, 6, 7, 8, 9 and 10. on the terminal strip found in the bottom left-hand side of the contactor box..